



## DA-4120 Series 4 Channels Digital Class-D Amplifier



### Features


- Switching power technology digital power amplifier
- Class-D PA power amplifier of minimum power consumption
- Less rack space and less heat generation
- Four channel power amplifiers into 19" rack mount unit
- Rated power output at 120W,240W,350W and 500W by four channels
- Four channel separate speaker outputs 4-16Ω/100V
- Balanced XLR input by phoenix connector for four channels
- Each input with separate gain control.
- Each four channel with high-cut filter.
- Built-in auto standby feature to save power consumption
- Separate four channel indicators for protection, clip, input and output
- Complete short circuit, overload, high temp, clip and DC protection
- Wide AC input from 110V to 230V

## Front Panel




- 1.PORT
- 2.CLIP
- 3.INPUT
- 4.OUTPUT
- 5.POWER
- 6.POWER SWITCH

## Rear Panel



1. AC POWER CORD
2. DC24V Battery Input
3. 100V SPEAKER OUTPUT
4. LINE INPUT
5. 8Ω SPEAKER OUTPUT
6. GAIN CONTROL
7. HIGH PASS FILTER
8. AUTO-STANDBY

## Diagram



## Specification

Description	Class-D Four Channel Power Amplifier			
Model	DA-4120	DA-4240	DA-4350	DA-4500
Rated Power Output	4x120W	4x240W	4x350W	4x500W
Speaker Output	8Ω & 100V			
Frequency Response	L/H Cut OFF 20Hz-20KHz (+1/-2dB) L/H Cut ON 70Hz-10KHz (+1/-3dB)			
Input	0.775V, 0dBu, balanced phoenix connector by four channels			
Input Impedance	10KΩ			
THD	<0.1% (1KHz/-3dBv, 100W)			
S/N Ratio	>80dB			
Crosstalk	>60dB, 1KHz, Max output			
Power Consumption	1200W			
Power Supply	Wide AC input from 110V & 230V, 50-60Hz			
Dimension	482(W)x420(D)x44(H) mm			
Weight	9.0kg			
Warranty	3 years warranty and free spare parts			